



Model:  
**quattro 1600**

max power 1580

**Overview:**

- Class AB power amplifier full MOSFET
- Unregulated power supply
- High level input with autosense power-on
- Cross Over with switchable High Pass or Low Pass filter
- Slot for X\_cards
- Remote Volume Control RTC (optional)

**Data:**

**POWER SUPPLY**

Power supply voltage	11 - 16V
DC-DC converter typology	Unregulated – Push Pull
Internal fuse	2 x 40A
Autosense power-on	in High level mode only
Overall efficiency	>60%

**OUTPUT POWER RMS**

Stereo power RMS @ 4Ω	150W x 4
Stereo power RMS @ 2Ω	210W x 4
Bridge power RMS @ 4Ω	420W x 2

**SIGNAL INPUT**

Input sensitivity range	0.35 ÷ 16V
Input impedance (High level mode)	47Ohm (floating)
Input impedance (Low level mode)	10kOhm (ground referenced)
Input CMRR	> 80dB
Input interface configuration	fully differential

**FEATURES**

Onboard crossover filter configuration	OFF - LP - HP
HP and LP filter range	20 ÷ 225Hz
HP and LP filter slope	12dB/oct
X-CARD compatibility	See catalogue

**CONNECTIONS**

Low level input	RCA
High level input	RCA
Remote control RTC (optional)	Modular jack

**APPEARANCE**

Dimensions	312x215x55mm
Weight	*.*Kg
Color	White
Finishing	Powder coating

**COMPATIBLE ACCESSORIES:**

X-CARDS  
RTC